

V-COM V30

HANDHELD 80 MHz

Handheld 80 MHz radio that is pre-programmed with Riks 1 and 2, and with the possibility of programming more channels. The radio has adjustable transmission power of 1/5 watt (Hi/Low), squelch adjustment, scanning, whisper mode and key lock. Clear LCD with indication of, among other things, transmission and battery level.

The radio is delivered complete in a cardboard box with charger/power supply, belt clip, antenna, battery and user manual. In addition, there is ProEquip's range of suitable accessories to connect to the radio.

FEATURES AND BENEFITS

- Small, light and handy radio
- 2.5/3.5 mm accessory socket with the possibility of connecting any accessory, examples are in the list below
- 1800 mAh Li-ion battery, for more than 8 hours of use (90/5/5)
- With Brodit active holder the radio is always easily accessible and charged
- Whisper mode; to increase microphone sensitivity
- With antenna adapter it is easy to connect an external antenna, for example an antenna with magnetic mount

OPTIONAL

30470	V-com V30 Belt clip
30471	V-com V30 Standard antenna 68 MHz
30472	V-com V30 Charger with power supply
30473	V-com V30 Battery 1800 mAh
30474	Brodit passiv holder, V-com V30
30475	Brodit aktiv holder, V-com V30
29585	ProEquip PRO-SP485 L Speaker microphone
29049	ProEquip PRO-D30L D-shell earpiece
29206	ProEquip PRO-AT35L Earpiece with acoustic hose
29115	ProEquip PRO-U610L 3-in-1 Earhanger/Peltor
18751	Antenna adapter SMA/f – BNC/f



SPECIFICATION

Frequency range:	68-88 MHz
Li-jon battery:	7,4 V /1800 mAh
Temperature range:	-20 till 60 °C
Accessory socket:	2,5/3,5 mm
Antenna connector:	SMA
RF-power:	5 W

MODEL	PART.NO
V-Com V30	30356

